

## Serial cable configuration.

- 1) 9 pins → 25 pins connector.

Computer DB9			Plotter DB25 S	
CD	1	_____	4	RTS
RXD	2	_____	2	TXD
TXD	3	_____	3	RXD
DTR	4	_____	5	CTS
		└───┘	6	DSR
SG	5	_____	7	SG
DSR	6	└───┘	20	DTR
CTS	8	_____		
RTS	7	_____	8	CD

- 2) 25 pins → 25 pins connector.

Computer DB25			Plotter DB25 S	
FG	1	_____	1	FG
TXD	2	_____	3	RXD
RXD	3	_____	2	TXD
RTS	4	_____	8	CD
CTS	5	_____	20	DTR
DSR	6	└───┘		
SG	7	_____	7	SG
CD	8	_____	4	RTS
DTR	20	_____	5	CTS
		└───┘	6	DSR

