

KA2206B

2.3W DUAL AUDIO POWER AMP

INTRODUCTION


The KA2206B is a monolithic integrated circuit consisting of a 2-channel power amplifier. It is suitable for stereo and bridge amplifier application of radio cassette tape recorder.

FEATURES

- High output power
Stereo : $P_O = 2.3W$ (Typ) at $V_{CC} = 9V$, $R_L = 4\Omega$.
Bridge : $P_O = 4.7W$ (Typ) at $V_{CC} = 9V$, $R_L = 8\Omega$.
- Low switching distortion at high frequency.
- Small shock noise at the time of power on/off due to a built-in muting circuit
- Good ripple rejection due to a built-in ripple filter.
- Good channel separation.
- Soft tone at the time of output saturation.
- Closed loop voltage gain fixed 45dB (Bridge : 51dB) but availability with external resistor added.
- Minimum number of external parts required.
- Easy to design radiator fin.

12-DIPH-300

16-DIP-300A



ORDERING INFORMATION

Device	Package	Operating Temperature
KS2206B	12-DIPH-300	-20°C ~ +70°C
KS2206BN	16-DIP-300A	

BLOCK DIAGRAM




Fig. 1

KA2206B**2.3W DUAL AUDIO POWER AMP****ABSOLUTE MAXIMUM RATINGS**

Characteristic	Symbol	Value	Unit
Supply Voltage	V_{CC}	15	V
Power Dissipation	P_D	4*	W
Operating Temperature	T_{OPR}	-20 ~ +70	°C
Storage Temperature	T_{STG}	-40 ~ +150	°C


* Fin is soldering on the PCB

ELECTRICAL CHARACTERISTICS(Ta = 25°C, V_{CC} = 9V, f = 1KHz, R_G = 600 Ω , unless otherwise specified)

Characteristic	Symbol	Test Conditions	Min	Typ	Max	Unit
Operating Supply Voltage	V_{CC}			9	11	V
Quiescent Circuit Current	I_{CCQ}	$V_I = 0$, Stereo		40	55	mA
Closed Loop Voltage Gain	G_{VC}	Stereo	43	45	47	dB
		Bridge	49	51	53	dB
Channel Balance	CB	Stereo	-1	0	+1	dB
Output Power	P_O	Stereo, $R_L=4\Omega$, THD = 10%	1.7	2.3		W
		$R_L=8\Omega$, THD = 10%		1.3		W
		Bridge, $R_L=8\Omega$, THD = 10%		4.7		W
Total Harmonic Distortion	THD	Stereo, $P_O=250mW$, $R_L = 4\Omega$		0.3	1.5	%
		Bridge		0.5		%
Input Resistance	R_I		21	30		K Ω
Ripple Rejection Ratio	RR	Stereo, $R_G=0\Omega$, $V_I=150mW$ f=100Hz	40	46		dB
Output Noise Voltage	V_{NO}	Stereo, $R_G=0\Omega$		0.3	1.0	mW
		Stereo, $R_G=10K\Omega$		0.5	2.0	mV
Cross Talk	CT	Stereo, $R_G=10K\Omega$, $V_O=0dBm$	40	55		dB

APPLICATION INFORMATION

1. Stereo application




i) Fixed voltage gain
(Pin 9 connected to GND directly)

$$G_V = 20 \log \left(\frac{R_1}{R_2} \right)$$

ii) Variable voltage gain
(RF and C1 connected with pin 9)

$$G_V = 20 \log \left(\frac{R_1}{R_2 + R_F} \right)$$

2. Bridge application



i) Fixed voltage gain (Pin 9 connected to GND directly)

$$G_V = 20 \log \left(\frac{R_1}{R_2} \right)$$

ii) Variable voltage gain (RF and C1 connected with pin 9)

$$G_V = 20 \log \left(\frac{R_1}{R_2 + R_F} \right)$$

SAMSUNG



ELECTRONICS

KA2206B

2.3W DUAL AUDIO POWER AMP

APPLICATION CIRCUIT

1. Stereo Amplifier



SAMSUNG

ELECTRONICS